

TECHNICAL DATA

Fluke i5sPQ3, 5 A AC Current Clamps, 3-pack



Key features

- Low level current clamp measures up to 5 A AC
- Compact shape makes transporting and storing convenient; the clamp measures only 116 x 43 x 23 mm (4.6 x 1.7 x .9 in)
- Take accurate readings without breaking the circuit
- CAT III 600 V (For insulated conductors only)

Product overview: Fluke i5sPQ3, 5 A AC Current Clamps, 3-pack

A pack of 3 pieces of the i5s current clamps, specially configured to provide low current accuracy while taking measurements on secondary current transformers. This cost-saving 3-pack is perfect for use with 3-phase tools such as the Fluke 434 or Fluke 435. The compact shape makes transporting and storing convenient. Takes accurate readings without breaking the circuit.

Specifications: Fluke i5sPQ3, 5 A AC Current Clamps, 3-pack

| Specifications | |
|---------------------------------|--------------|
| Nominal current range | 5 A |
| Continuous current range | 10 mA to 6 A |
| Maximum non-destructive current | 70 A |

| | | |
|--|---|----------------|
| Lowest measurable current | 10 mA | |
| Basic accuracy | | 48 Hz to 65 Hz |
| | 10 mA to 1 A | 1% + 5 mA |
| | 1 A to 5 A | 1% |
| Useable frequency | 40 Hz to 5 kHz | |
| Output level(s) | 400 mV/A | |
| Input load impedance | > 1 MΩ in parallel with up to 47 pF | |
| Crest factor | ≤ 3, add 0.7% to accuracy | |
| Safety specifications | | |
| Safety | CAT III 600 V per IEC/EN61010-1, Pollution Degree 2 | |
| Maximum voltage | 600 V AC | |
| Mechanical and General Specifications | | |
| Warranty | 1 year | |
| Maximum conductor diameter | 15 mm | |
| Output cable length | 2.5 m | |
| BNC adapter | Yes | |
| BNC to banana adapter included | No | |

Ordering information



Fluke i5sPQ3

5 A ac Current Clamps, 3-pack

Fluke. *Keeping your world up and running.®*

Fluke Europe B.V.

P.O. Box 1186
5602 BD Eindhoven
The Netherlands
www.fluke.com/en

©2023 Fluke Corporation. All rights reserved.
Data subject to alteration without notice.
09/2023

For more information call:

In Middle East/Africa
+31 (0)40 267 5100

**Modification of this document is not permitted
without written permission from Fluke Corporation.**